

Dynalabs 放大器是一种完全集成、紧凑且高效的双通道音频功率转换解决方案。它是为控制振动测试系统而开发的。

SA-1100 放大器用于 PM-440、MS-440、PM-250 和 MS-250 激振器。



## DYN-SA-1100:

Adjustable gain	Yes
External Signal Input	Yes
Input Protection	Yes
Sine Freq. Generator	Activated by pulling out the gain knob
Sine Frequency Range	0-15 kHz
Operation Voltage	110 V – 220 V
Dimensions W x H x D (mm)	310 x 80 x 275mm
Amplifier weight	5.3 kg
External Input Voltage	10 VAC (Peak)
Max Voltage Gain (1kHz)	32 Db
Output impedance	@1kHz:11mohm
Input impedance	1.88 kohm
AC Output	160 V
Frequency response variance	20 Hz-20 kHz:±2Db
Current Limiting (Load current)	/
Current Limiting (Peak output)	30 A

## Technical Drawings:

